

## 1200VA Voltage Regulator - Automatic voltage regulation with surge protection

NÚMERO DE MODELO: VR1208R



### Destacado

- Automatic voltage regulation (AVR) and AC surge suppression
- Maintains regulated 120V nominal output over an input range of 100 to 145V
- 1200 VA
- 8 NEMA 5-15R outlets, 3 foot AC cord
- LEDs display boost, cut and normal operation

### El Paquete Incluye

- VR1208R Line Conditioner
- Instruction manual with warranty information

### General

1200 VA Automatic Voltage Regulation (AVR) system/Protects sensitive electronics, computer accessories and home theater equipment from power-related damage and performance problems/Extends the useful life of connected equipment by providing optimum voltage conditions for enhanced efficiency and cooler internal operating temperatures/Reliable transformer-based voltage correction circuits maintain 120V nominal output during voltage fluctuations between 100 and 145V/Two levels of voltage stabilization offer targeted response for overvoltages and brownouts/Prevents equipment damage and power related performance problems for computer accessories, printers, home theater equipment, a/v components and other sensitive electronic devices/AC surge and EMI/RFI noise suppression/Supports loads up to 1200 VA, 8 AC outlets/3 ft AC line cord/3 diagnostic LEDs display boost, cut and normal operation.

### Características

- Maintains regulated 120V (+12%/-12%) nominal output over an input range of 100 to 145V
- Protects sensitive electronics, computer accessories and home theater equipment from power-related damage and performance problems
- Extends the useful life of connected equipment by providing optimum voltage conditions for enhanced efficiency and cooler internal operating temperatures
- Two levels of voltage stabilization offers response to overvoltages and brownouts
- Input voltages over 130V are reduced by 12% (+/- 3V)
- Input voltages below 110V are boosted by 12% (+/- 3V)
- 1200 VA output power
- EMI/RFI noise filtering prevents equipment interaction, system interference, lockups and other power-related audio and video artifacts
- 3 diagnostic LEDs indicate boost, cut and normal AVR operation
- 8 protected NEMA5-15R outlets
- 3 foot AC power cord with NEMA5-15P input plug

## Especificaciones

SALIDA



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

Voltaje(s) Nominal(es) de Salida Soportado(s)	120V
Tomacorrientes	(8) 5-15R
Salida (VA)	1200
Voltaje Nominal de Salida	120V / 60Hz
Detalles del Tomacorrientes	4 AVR / Surge NEMA 5-15R outlets; 4 Surge-only NEMA 5-15R outlets
<b>GARANTIA</b>	
Periodo de Garantía del Producto (A Nivel Mundial)	2-year limited warranty

© 2016 Tripp Lite. Todos los Derechos Reservados.